

# PS-1201AC

## AC Power Switch

### Package Content

1. PS-1201AC



### Features

- ◆ Support wide AC voltage range 90 ~ 235V
- ◆ Built-in high level fuse for fire protection
- ◆ Able to work with Controller for further integration
- ◆ Support the current up to 10A
- ◆ Support setting recovery mode to avoid any unexpected power lost
- ◆ Support RF Remote control (optional)
- ◆ Also can be used in lighting control

### SPECIFICATION & I/O INTERFACE

RS-485	1 x 2pins-phoenix terminal block For RS-485 only
AC Power I/O	90 ~ 235V
LED light	Power Indication

### Others

Power Supply	AC 90~235V
Power Consumption	3W
Operation Temp.	-20°C to 75°C (4°F to 167°F)
Storage Temp.	-40°C to 85°C (-40°F to 185°F)
Fixedness	Mounting ear with screws
Dimension	92x 49x 34mm



- 1) RS-485**  
Connect to device with 485
- 2) AC Input**  
Connect to AC input
- 3) AC Input / AC Output**  
Connect to AC input & output
- 4) AC Output**  
Connect to AC output